

# E2-SETC22

**NEW**

## LED Exit Sign Combo with Emergency Battery Backup



adjustable light heads



test button & indicator light



### PRODUCT DESCRIPTION:

The E2-COMBO LED Exit Sign is of the latest versions of this industry standard. This sign combines emergency exit lights and the exit sign together, with an integrated emergency battery backup, into one fixture. The 1.2W LED light heads are adjustable and can be aimed to the best desired angle. This sign is also equipped with a self diagnostic test button and an indicator light showing that the emergency battery backup system is operating properly.

### FEATURES AND STANDARDS:

- Dual 120/277 voltage
- Indirect placement for diffused legend output
- Flame-Retardant, High-Impact, Thermoplastic Housing
- Ceiling or Back Mount
- Integrated Solid State System
- Constant Current, Controlled Automatic Charger Circuit
- Low-Voltage Battery Cutoff
- Brownout Sensitivity
- Maintenance-Free Rechargeable Sealed Nickel Cadmium Battery
- Test Switch
- Led (power On) Indicator



**WARRANTY**  
5 Year Warranty

18"



11 5/8"

1 3/4"



7 1/8"

Product Number	Wattage	Color	Certifications	Dimmable	Voltage	Lumens	Working Hours	CRI
E2-SETC22	4W @ 120, 5.2W @ 277V	RED	UL DAMP LOCATION LISTED	NO	120- 277V		EMERGENCY MODE-90min.	

**Ceiling Mount**



**Wall Mount**



\* must connect internal battery before fixture installation