


E2-EX-119 LED EXIT SIGN LAMP HEADS

NEW

Test Button & Indicator Light

16.92inch



PRODUCT DESCRIPTION:

The E2-EX-119 Exit Sign with remote lamp heads and integrated emergency battery backup is of the latest versions of this industry standard. The 1.2W LED remote heads are adjustable and can be aimed to the best desired angle. This sign is also equipped with a self diagnostic test button and an indicator light showing that the emergency battery backup system is operating properly.

FEATURES AND STANDARDS:

- Injection-molded thermoplastic ABS housing 5VA flame rating.
- Innovative, easy installation in minutes.
- Red letters.
- Double face.
- 120/277VAC dual voltage operation.
- 2*1.2w LEDs lamp heads. 6500K
- Built-in 3.6V 700mAh rechargeable Ni-cd battery for minimum 90 minutes emergency operation.
- Maximum 24 hours full recharge time.
- Test switch and charge indicator.
- UL and CUL listed.

WARRANTY:

E2 warrants that our LED products will be free from defects in materials and workmanship for a period of five (5) years from the date of delivery to the end user, including coverage of light output, color stability, driver performance and fixture finish. Please see our complete warranty terms located at www.e2lightingusa.com.



E2-EX-119

LED EXIT SIGN - DUAL FACE LAMP HEADS

Page: 2 of 2

Product Number	Wattage	Color	Certifications	Dimmable	Voltage	Lumens	Working Hours	CRI
E2-EX-119	4W @ 120, 5.2W @ 277V	RED	UL DAMP LOCATION LISTED	NO	120- 277V		EMERGENCY MODE-90min.	